

Optimus Yellow Data Logging Sound Level Meter



Features

- Simple to use
- Simultaneous measurement of all parameters
- 120 dB measurement range
- Data logging with VoiceTag (audio notes)
- A, C and Z weightings
- Fast, Slow and Impulse response
- Bluetooth connection to mobile app

Applications

- Basic noise surveys
- Noise ordinance enforcement
- Fire alarm testing
- Machinery maintenance and trouble-shooting

Optimus Yellow

The CR15xB Optimus Yellow is a calibrated, professional grade sound level meter for noise measurements that must meet the relevant international standards. Despite being a powerful meter it is extremely easy to use, ensuring you get the correct measurements from the start.

The Optimus range of sound level meters uses the latest display technology and digital signal processing (DSP) techniques to provide you with a very powerful yet easy to use meter. The ease of use comes from the fact that all parameters are automatically measured at the same time, so no need to think about what you need in the split second before starting the measurement.

Making Noise Measurements

Making measurements usually consists of checking the calibration (adjustments are automatic), recording a voice tag if required, and then taking the readings.

As this meter is a data logger all the measurement parameters are stored along with time, date and other relevant information.

Future Upgrade

If you decide at a later date that you need an Integrating sound level meter or even octave band filters then we offer a simple upgrade path.

These features can be added at a later date. Some can even be fitted without returning the meter to the factory by remote update.

We can even change the meter from Class 2 to Class 1, although of course it must be returned for this upgrade.

Visit the **Options** tab for more details.

Optimus Yellow Data Logging Sound Level Meter

Specifications

Standards	IEC 61672-1:2013 Class 1 or Class 2 IEC 61672-1:2002 Class 1 or Class 2 Group X IEC 60651:2001 Type 1 I or Type 2 I ANSI S1.4 -1983 (R2006), ANSI S1.43 - 1997 (R2007) ANSI S1.25:1991	Connections	USB Type B to PC AC & DC Output via ZL:174 (2 x Phono, 1m) Multi-pin IO for external power via ZL:171 cable (2.1mm socket) External Power: 5v-15v via MultiIO socket via ZL:171 cable (2.1mm socket)
Microphone	Class 1 MK:224 pre-polarized, Class 2 MK:216 pre-polarized	Tripod Mount Case	1/4" Whitworth socket Material: High Impact ABS-PC with soft touch back & keypad
Measurement Range	20dB to 140dB RMS Single Range	Environmental	Temperature: Operating -10°C to +50°C, Storage -20°C to +60°C
Noise Floor	<18dB(A) Class 1, <21dB(A) Class 2		
Frequency Weightings	RMS & Peak : A, C, & Z Measured Simultaneously	Electromagnetic performance	Humidity: Up to 95% RH Non Condensing IEC 61672-1:2002 & IEC 61672-2:2003 Except where modified by EN 61000-6-1:2007 & EN 61000-6-1:2007
Time Weightings	Fast, Slow & Impulse Measured Simultaneously	Language options	English, French, German, Spanish. Other language options may be available
Display	High resolution display. Ambient light sensor & illuminated keypad	Software Support	NoiseTools Download, Configuration & Analysis software supplied as standard. Compatible with Microsoft Windows XP, Vista, 7, 8 & 10 (32bit & 64bit)
Memory	4GB, 32GB factory fit option		
Time History	10ms, 62.5ms, 125ms, 250ms,	Displayed Functions	LXY, LXYSMax, LXYSMin, Run Time
Data Rates	1/2 sec, 1 sec, 2 sec (User selectable)	Stored Functions	LXYSMax & Time History of LXYSMax, Start Time
VoiceTag Audio Recording	Up to 30 seconds of audio notes with each measurement		
Dimensions	Size: 283mm x 65mm x 30mm		
Weight	300gms/10oz		
Power	4 x AA Alkaline Typically 12 hours with Alkaline AA Typically 20 hours with Lithium AA Non-Rechargeable External Power: 5v-15v via MultiIO socket via ZL:171 cable (2.1mm socket)		

Head Office

NoiseMeters Inc
3233 Coolidge Hwy
Berkley
MI 48072
USA

Telephone **888 206 4377**
Fax **888 584 2230**

Email: info@noisemeters.ca
Support: support@noisemeters.ca

Web Sites

Main site:
<https://www.noisemeters.ca>

Product shortcut:
<https://www.noisemeters.ca/p/cr152b/>

Tech Support:
<https://support.noisemeters.com>

where x=A ,C ,Z; y= F, S, I